



Alarmcom Leptonics Pty Ltd

800 Parramatta Road,

Lewisham, NSW, 2049

Ph: (02)9564 6363

Fax: (02) 9564 6331

Programming PC1550 to Force Dial

N.B. This method should be used if a feature such as Telstra's Message Bank, or any other service that alters the dial tone at any time, is put on the same telephone line as the PC1550.

Enter Programming mode (**[*] [8] [1500]**) then enter the following.

[00] [046] [*3*] [Phone Number 1] [*6*] [#] [#]

This will exit programming. Re-enter programming mode (**[*] [8] [1500]**) then enter the following.

[00] [055] [*3*] [Phone Number 2] [*6*] [#] [#]

Important, please note the following:

1. This procedure must be done at least 1 minute after the panel is powered up, any sooner than one minute will not work.
2. After this procedure is done, **do not** enter the regular programming section for the phone numbers. This will erase the phone number that you have already entered above.
3. DO NOT program section 01 and 03